

**Series:** COMPACT-FAN Type D/DS  
 EC-MOTOR  
 double inlet  
 with forward curved blades

**FISCHBACH**  
 Luft- und Ventilatorentechnik GmbH

**Type:** DS9-070/DM5

ERP KONFORM

CE -conform

UK  
 CA




**manufacturer:**

Fischbach Luft- und Ventilatorentechnik GmbH  
 Am Hellerberg 22-24  
 D-57290 Neunkirchen  
 phone:  
 telefax:  
 internet:  
 email:

++49(0)2735/777-0  
 ++49(0)2735/770-133  
 www.fischbach-luft.de  
 info@fischbach-luft.de


**Technical Data**

weight:	(kg)	82
material housing:	steel, galvanized	
material impeller:	steel, galvanized	
direction of rotation:	left	
motor protection class:	IP 65	
insulation class:	F	
motor protection:	thermal contact	



\*external dimension of discharge

**connection plan\***  
 FFU-EC 400



\* Connection only according to the enclosed technical documentation.

the silent one



**Series: COMPACT-FAN Type D/DS**  
**EC-MOTOR**  
 double inlet  
 with forward curved blades

**FISCHBACH**  
 Luft- und Ventilatorentechnik GmbH

**Type: DS9-070/DM5**

Erp 2013 2015 x 2018


**Performance data**

main voltage:	(V)	400 (3~)
frequency:	(Hz)	50
current max.:	(A)	14,7
power input max.:	(kW)	8,3
air flow volume max.:	(m³/h)	14222
statical pressure max.:	(Pa)	895
speed max.:	(rpm)	1200
supply air temperature:	(°C)	-25... +45
capacitor:	(µF)	-

**ErP-Data:**

total efficiency fan ( $\eta_e$ ):	(%)	45,5
installation category:		A
efficiency category:		static
efficiency grade: N	(%)	44
target efficiency ( $\eta_{target}$ ):	(%)	40,4
speed controller		yes
year of manufacturing		since 2015
manufacturer:	Fischbach Luft- und Ventilatorentechnik GmbH D-57290 Neunkirchen / HRB 5804 Siegen	
order no.		18111980
power input:	(kW)	2,66
air flow volume:	(m³/h)	5180
statical pressure:	(Pa)	795
speed:	(rpm)	1200
specific ratio:		1

disassembling/recycling/disposal: see page decommission  
 installation/operation/maintenance: see operating and mounting instructions  
 measurement for determination of efficiency without additional items



control with	type	order-Nr.
FISCHBACH-frequency-converter	FFU3-21-11	63775
FISCHBACH-Pre-set 0-10V (optional accessories)	FS 10	69460

Technical documentation according to page: **General information**